

# WiiM Amp

## Versatile Streaming Amplifier

Easily integrate the WiiM Amp with your classic passive speakers, TV, or record player to unlock a world of sound. Stream your music collection effortlessly directly from any music application such as Apple AirPlay 2, Google Chromecast, Alexa Music Cast, DLNA, Spotify Connect, TIDAL Connect, plus much more.

The WiiM Amp packs 60 watts per channel (8 ohms) or 120 Watts per channel (4 ohms), it delivers high-fidelity sound to even the most demanding speakers, up to four on a single amplifier.

These features guarantee a fantastic audio experience in Hi-Res, lossless quality, and allows music to be played in multiple rooms at the same time.



### Physical

- LED: Three-color LED indicates device status and six white LEDs for the volume indicator.
- Volume knob: Adjust volume/play/play pause button.
- Colors: Grey ● Silver ●

Weight  
4.1lbs (1860g)

Dimensions (H x W x D)  
190x190x63 mm (7.5x 7.5x 2.4 inches)



Grey ●

### Tech Specs

#### Amplifier

- Class-D digital amplifier
- 60 W/channel (8 ohms), 120 W/channel (4 ohms)

#### Input

- Analog (RCA), digital Optical port, HDMI ARC, up to 24-bit/192 kHz

#### Output

- Up to 192 kHz/ 24-bit, varying sample rate and bit depth based on the audio source without resampling
- Subwoofer output-Adjustable crossover frequency,

#### Two banana plugs

- NR: 99 dB
- THD+N (1 kHz), 5W/8 Ohms: -95 dB

#### Connectivity and Power

- AC 100-240v input
- Wi-Fi 5, 802.11 b/g/n/ac 2.4 GHz and 5 GHz dual band
- Bluetooth 5.0 with BLE, supports both A2DP receiver and transmitter, AVRCP, HID, works with the WiiM Voice Remote
- Ethernet, 10M/100 Mbps
- USB Host – connect to USB disk for local music playback.

**U.S. MSRP: \$299**

**Preorder Now!**